









Jackery Explorer 240



-  Phone
24Charges (iPhone 8)
-  Drone
4Charges (60W)
-  Light
40H (5W)
-  Laptop
3.5Charges (Macbook Pro13)
-  50" TV
3H (60W)
-  Fan
15H (15W)
-  Camera
11Charges (10W)
-  Electric Blanket
4H(55W)

SPECIFICATION		WHAT'S IN THE BOX
Capacity	240Wh	 1* Explorer 240 Portable Power Station (240Wh)
Continuous Output	200W	
Peak Output	400W	
Charged with AC Adapter	Li-ion NCM	
Charged with 12V Car Outlet	After 1000 cycles, ≥ 80% capacity remains	
Charged with Solar Panel	6.6lbs (3KG)	
Battery Lifecycles	9.05 x 5.24 x 7.87 in (23 x 13.32 x 20 cm)	
Output Ports	AC Output (*1): 240VAC, 50Hz, 200W Rated(400W Surge Peak) Car Port Output(*1); 12V/10A USB-A Output (* 2):5V/2.4A	 1* Car Charger Cable
Input Ports	8mm DC Input (*1):19V/3.42A (support 12~30V)	 1* AC Charger Cable
PACKAGE		 1* User Manual
Box Size	9.05 x 5.24 x 7.87 in (23 x 13.32 x 20 cm)	
Weight with Box	3.45kg / 7.6lbs	
Qty/ Carton	1pcs/carton	
GW	4.33kg / 9.546lbs	
Carton Size	10.75x6.81x11.42in (27.3x17.3x29cm)	
RECHARGING TIME TO 100%		
Charged with AC Adapter	3.5 H	
Charged with 12V Car Outlet	5.5 H	
Charged with Solar Panel	5.5 H (1*100W Panel)	
RECOMMENDED COMBO		



1*Explorer 240 + 1*SolarSaga 80



1*Explorer 240 + 1*SolarSaga 100